

## REISSUE PATENT APPLICATION TRANSMITTAL

ADDRESS TO:

Assistant Commissioner for Patents  
Box Reissue  
Washington, D.C. 20231

Attorney Docket No.

2037.1005-002

First Named Inventor

Peter B. Gillingham

Original Patent Number

5,283,761

Original Patent Issue Date  
(Month/Day/Year)

February 1, 1994

Express Mail Label No.

EL531544795US

APPLICATION FOR REISSUE OF:



Utility Patent



Design Patent



Plant Patent

(Check applicable box)

Title of  
Invention

METHOD OF MULTI-LEVEL STORAGE IN DRAM AND APPARATUS THEREOF (As Amended)

## APPLICATION ELEMENTS

## ACCOMPANYING APPLICATION PARTS

1. ☒ Fee Transmittal Form  
(Submit an original, and a duplicate for fee processing)
2. ☒ Specification and Claims (amended, if appropriate)
3. ☒ Drawing(s) (proposed amendments, if appropriate)
4. ☒ Reissue Oath / Declaration (original or copy) / POA  
(37 C.F.R. 1.175)
5. ☐ Original U.S. Patent
- ☐ Offer to Surrender Original Patent (37 C.F.R. 1.178)
- or ☐ Ribboned Original Patent Grant
- ☐ Affidavit / Declaration of Loss
6. ☒ Original U.S. Patent currently assigned?  
☒ Yes ☐ No  
(If Yes, check applicable box(es))
- ☒ Written Consent of all Assignees
- ☒ 37 C.F.R. 3.73(b) Statement ☐ Power of Attorney

7. ☐ Transfer drawings from Patent File
8. ☐ Foreign Priority Claim (35 U.S.C. 119)  
(if applicable)
9. ☒ Information Disclosure Statement (IDS)/PTO-1449 ☐ Copies of IDS Citations
10. ☐ English Translation of Reissue Oath / Declaration  
(if applicable)
11. ☐ Small Entity Statement(s) ☐ Statement filed in prior application,  
Status still proper and desired
12. ☐ Preliminary Amendment
13. ☒ Return Receipt Postcard (MPEP 503) (2)  
(Should be specifically itemized)
14. ☒ This is a broadening Reissue, broadened claim(s) included  
(within 2 years of issue date)
15. ☐ Other: .....

## 15. CORRESPONDENCE ADDRESS

NAME

James M. Smith, Esq.  
HAMILTON, BROOK, SMITH & REYNOLDS, P.C.

ADDRESS

Two Militia Drive

CITY

Lexington

STATE

MA

ZIP CODE

02421-4799

COUNTRY

USA

TELEPHONE

(781) 861-6240

FAX

(781) 861-9540

Signature

Gerald M. Bluhm

Date

9/1/00

Submitted by  
Typed or Printed Name

Gerald M. Bluhm

Reg. Number

44,035

::ODMA\HODMA\Manage;155425;1

JMS/GMB/dlc

08/18/00

PATENT APPLICATION  
Docket No.: 2037.1005-002

## IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

Applicant: Peter B. Gillingham

Reissue Application of U.S. Patent 5,283,761, Issued February 1, 1994

For: METHOD OF MULTI-LEVEL STORAGE IN DRAM AND  
APPARATUS THEREOF (as amended)Jc639 U.S. PTO  
09/654367  
09/01/00Date: ~~8-29-00~~ 9-1-00

EXPRESS MAIL LABEL NO. EL551544795US


WRITTEN CONSENT OF ASSIGNEE IN CONTINUATION  
OF REISSUE APPLICATIONAssistant Commissioner for Patents  
Washington, D.C. 20231

Sir:

Mosaid Technologies Incorporated is the assignee of the referenced patent application and does hereby consent to the referenced continuation of reissue patent application.

A Certificate under 37 C.F.R. §3.73(b) certifying that, to the best of my knowledge and belief, title is in Mosaid Technologies Incorporated is being filed concurrently with this Written Consent.

Respectfully submitted,



~~George Cwynar~~ Peter Gillingham  
President VP Business Development  
Mosaid Technologies Incorporated  
11 Hines Road  
Kanata, Canada K2K 2X1

Date: 21 August 2000

<b>REISSUE APPLICATION FEE TRANSMITTAL FORM</b>						Docket Number (Optional) 2037.1005-002		
<b>Claims as Filed - Part 1</b>								
Claims in Patent	For	Number Filed in Reissue Application	(3) Number Extra	Small Entity		Other than a Small Entity		
				Rate	Fee	Rate	Fee	
(A) 41	Total Claims (37 CFR 1.16(j))	(B) 10	**** 0 =	x \$	=	or	x \$ = 0	
(C) 9	Independent Claims (37 CFR 1.16(i))	(D) 2	* 0 =	x \$	=		x \$ = 0	
Basic Fee (37 CFR 1.16(h))				\$			\$ 690	
Total Filing Fee				\$		OR	\$ 690	
<b>Claims as Amended - Part 2</b>								
	(1) Claims Remaining After Amendment		(2) Highest Number Previously Paid For	(3) Extra Claims Present	Small Entity		Other than a Small Entity	
					Rate	Fee	Rate	Fee
Total Claims (37 CFR 1.16(j))	***	MINUS	**	=	x \$	=	or	x \$ =
Independent Claims (37 CFR 1.16(i))	***	MINUS	*****	=	x \$	=		x \$ =
Total Additional Fee				\$		OR	\$	
<p>* If the entry in (D) is less than the entry in (C), Write "0" in column 3.</p> <p>** If the "Highest Number of Total Claims Previously Paid For" is less than 20, Write "20" in this space.</p> <p>*** After any cancelation of claims</p> <p>**** If "A" is greater than 20, use (B - A); if "A" is 20 or less, use (B - 20).</p> <p>***** "Highest Number of Independent Claims Previously Paid For" or Number of Independent Claims in Patent (C).</p>								
<p><input type="checkbox"/> Please charge Deposit Account No. _____ in the amount of _____. A duplicate copy of this sheet is enclosed.</p> <p><input type="checkbox"/> The Commissioner is hereby authorized to charge any additional fees under 37 CFR 1.16 or 1.17 which may be required, or credit any overpayment to Deposit Account No. _____. A duplicate copy of this sheet is enclosed.</p> <p><input checked="" type="checkbox"/> A check in the amount of \$ <u>690</u> to cover the filing / additional fee is enclosed.</p>								
<u>8/29/00</u> Date		<u>Derek R. M. 44,035</u> Signature of Applicant, Attorney or Agent of Record  <u>Gerald M. Bluhm</u> Typed or printed name						

<b>REISSUE APPLICATION FEE TRANSMITTAL FORM</b>						Docket Number (Optional) 2037.1005-002		
<b>Claims as Filed - Part 1</b>								
Claims in Patent	For	Number Filed in Reissue Application	(3) Number Extra	Small Entity		Other than a Small Entity		
				Rate	Fee	Rate	Fee	
(A) 41	Total Claims (37 CFR 1.16(j))	(B) 10	**** 0 =	x \$	=	or	x \$ = 0	
(C) 9	Independent Claims (37 CFR 1.16(i))	(D) 2	* 0 =	x \$	=		x \$ = 0	
Basic Fee (37 CFR 1.16(h))					\$		\$ 690	
Total Filing Fee					\$	OR	\$ 690	
<b>Claims as Amended - Part 2</b>								
	(1) Claims Remaining After Amendment		(2) Highest Number Previously Paid For	(3) Extra Claims Present	Small Entity		Other than a Small Entity	
					Rate	Fee	Rate	Fee
Total Claims (37 CFR 1.16(j))	***	MINUS	**	=	x \$	=	or	x \$ =
Independent Claims (37 CFR 1.16(i))	***	MINUS	*****	=	x \$	=		x \$ =
Total Additional Fee					\$	OR	\$	
<p>*** If the entry in (D) is less than the entry in (C), Write "0" in column 3.</p> <p>*** If the "Highest Number of Total Claims Previously Paid For" is less than 20, Write "20" in this space.</p> <p>*** After any cancelation of claims</p> <p>*** If "A" is greater than 20, use (B - A); if "A" is 20 or less, use (B - 20).</p> <p>***** "Highest Number of Independent Claims Previously Paid For" or Number of Independent Claims in Patent (C).</p>								
<p><input type="checkbox"/> Please charge Deposit Account No. _____ in the amount of _____. A duplicate copy of this sheet is enclosed.</p> <p><input type="checkbox"/> The Commissioner is hereby authorized to charge any additional fees under 37 CFR 1.16 or 1.17 which may be required, or credit any overpayment to Deposit Account No. _____. A duplicate copy of this sheet is enclosed.</p> <p><input checked="" type="checkbox"/> A check in the amount of \$ <u>690</u> to cover the filing / additional fee is enclosed.</p>								
<u>8/29/00</u> Date		<u>Derek R. Hill 44,075</u> Signature of Applicant, Attorney or Agent of Record						
<u>Gerald M. Bluhm</u> Typed or printed name								

## METHOD OF MULTI-LEVEL STORAGE IN DRAM

This is a continuation of Reissue Application Ser. No. 08/595,020, filed January 31, 1996, which is based on original U.S. Pat. No. 5,283,761 issued February 1, 1994.

## FIELD OF THE INVENTION

This invention relates to dynamic random access memory (DRAM) memories, and in particular to a method of storing a variable level signal in each cell of a DRAM for representing more than one bit in each cell.

## BACKGROUND TO THE INVENTION

To store for example two bits in a DRAM cell, it must be able to store four different voltage levels. A problem with such cells, is that noise margins are reduced to one-third that of a one bit per cell DRAM, which is too low to withstand the occasional  $\alpha$ -particle hit.

A second problem with multi-bit storage cells relates to the method of sensing. No simple method of sensing has previously been designed, although attempts have been made to solve this problem, e.g. as described in the publication by M. Aoki et al, "A 16-Levels/Cell Dynamic Memory", ISSCC Dig. TECH. Papers 1985, pp 246-247, and in T. Furuyama et al, "An Experimental Two-Bit/Cell Storage DRAM for Macrocell or Memory-On-Application", IEEE Journal of Solid State Circuits, Vol. 24, No. 2, pp 388-393, April 1989. The technique described by Aoki cannot use normal sense amplifiers. It requires a precision analog D to A converter to implement a staircase waveform and a charge amplifier to sense data. The technique described by Furuyama requires the generation of precision reference levels to distinguish between four levels. These levels are not self-compensated for offsets developed in the sensing operation, and this method suffers from poor signal margin. Hidaka et al describe a technique for simultaneously reading two cells at a time in the article "A divided/Shared Bitline Sensing Scheme for 64Mb DRAM Core" in the 1990 Symposium on VLSI Circuitry 1990, IEEE, p. 15, 16 which while describing dividing a bitline, is not related to multiple bit storage in a single cell.

DRAMs have previously been built with cells holding up to sixteen bits of storage, e.g. in the aforementioned article by M. Aoki et al, for use in file memories. A 4 K test array is believed to have been the largest memory built using this design. Leakage characteristics of the DRAM cell were required to be very tightly controlled and even then, accurate sensing of the small voltage differences between levels becomes very difficult. Another problem with this scheme was the length of time required to access: a single read cycle required 16 clocks for the read followed by 16 clocks for the restore.

To implement a 2 bit DRAM, one can define the cell as storing one of four voltage levels  $V_{cell0}$ ,  $V_{cell1}$ ,  $V_{cell2}$  and  $V_{cell3}$ , and reference voltage midpoints between these four voltage, which can be defined as  $V_{ref1}$ ,  $V_{ref2}$  and  $V_{ref3}$ . These midpoints can be referred to, to differentiate between the four voltage levels. The relative voltage of these levels are shown in Table 1 below.

STORAGE VOLTAGES	REFERENCE VOLTAGES	ACTUAL VOLTAGE
$V_{cell1}$	$V_{ref3}$	$V_{DD}$
		$5/6 V_{DD}$
$V_{cell2}$		$2/3 V_{DD}$

-continued

STORAGE VOLTAGES	REFERENCE VOLTAGES	ACTUAL VOLTAGE
	$V_{ref2}$	$1/2 V_{DD}$
$V_{cell1}$		$1/3 V_{DD}$
	$V_{ref1}$	$1/6 V_{DD}$
$V_{cell0}$		$V_{SS}$

The storage voltages are the actual voltages stored in the cells, although the sensing voltages are somewhat more attenuated. Since sensing takes place on the bitlines which divide cell charge by the cell to bitline capacitance ratio, much lower voltages than those in the cell are actually sensed. In a standard DRAM, these voltage differences are in the order of 100-300 mV. It is the voltage midpoints between these smaller signals that must finally be generated to allow for correct sensing.

Furuyama et al in the article noted above describes one method of sensing these voltages. Furuyama et al used three sense amplifiers and three approximate midpoint sensing voltages. The cell charge is shared with the bitline, the bitline is split into three sections (sub-bitlines) and three sense amplifiers determine whether the cell charge is above or below their particular reference voltages. This data is then converted to two bits and a resulting output. Reconversion of the two bits allows approximate values to be driven into the bitline so that restore takes place after the read cycle. A write cycle operates in the same way as the restore section of the read cycle.

It should be noted that since the cell shares charge with three sub-bitlines, and the reference cell with only one sub-bitline, the reference voltage is about three times larger than it should be for sensing, casting doubt on the operability of this design. Secondly, three sense amplifiers are used, and since sense amplifiers have been growing proportionally larger and larger with each generation of memory, a minimum of sense amplifiers is desirable. A third problem is that the reference voltage

is not stored on a cell whose [leakage does not] characteristics track the leakage of the data cells, introducing another source of error into the circuit.

#### SUMMARY OF THE PRESENT INVENTION

In the present invention a method and circuit has

been designed which substantially solves some of the above-identified problems. Only two sense amplifiers are required[, which generate the sensing voltages at the time of sensing]. In the present invention each bitline is split exactly in half, rather than into thirds, by use of a switch. The [noise margins are relatively large, equivalent to that of a standard DRAM maintaining reliability, and the] present design can be used as a standard one bit per cell DRAM as an alternative to a multiple bit per cell DRAM, which increases its universality, allows it to be used in present designs, and increases yield.

In accordance with an embodiment of the present invention, a method of processing data having one of four levels stored in a DRAM cell is comprised of sensing whether or not the data voltage is above or below a voltage level midway between a highest and a lowest of the four levels, setting the voltage on a reference line higher than the lowest and lower than the next highest of the four levels in the event the data voltage is below the midway voltage level, setting the voltage on the reference line higher than the second highest and lower than the highest of the four levels in the event the data

In accordance with an embodiment of the present invention, a method of processing data having one of plural levels stored in a DRAM cell capacitor is comprised of dumping the charge of the cell capacitor on a first of a pair of conductors of a folded bitline, maintaining the other of the pair of conductors split into other sub-bitline conductors and charging each of the other sub-bitline conductors to an intermediate voltage, splitting the first of the conductors into first sub-bitline conductors, sensing the sub-bitlines to determine whether the charge of the cell has a higher voltage than the intermediate voltage of one of the other sub-bitline conductors and providing a logic level result signal, storing the logic level result signal in a dummy cell capacitor, setting a charge storage capacitor and all of the sub-bitlines other than the first sub-bitline maintaining a voltage resulting from the dumped charge to a predetermined voltage, dumping charge stored in the dummy cell capacitor on the sub-bitlines and charge storage capacitor, thereby varying the predetermined voltage stored thereon to a degree related to the capacities of the dummy cell capacitor, the charge storage cells and the predetermined voltage, to a level above or below the intermediate level, isolating the sub-bitlines, applying the intermediate voltage to one of the other sub-bitline conductors, comparing the cell voltage on one sub-bitline with the voltage on the other sub-bitline carrying the level above or below the intermediate level to obtain a first logic bit, and comparing the voltages carried by the other sub-bitlines to obtain a second logic bit, whereby the first and second logic bits are indicative of one of four logic states corresponding to one of the plural levels stored in the DRAM cell.

A better understanding of the invention will be obtained by reference to the detailed description below, in conjunction with the following drawings, in which:

FIG. 5 is a schematic diagram illustrating an embodiment of the invention, and

## DETAILED DESCRIPTION OF THE INVENTION

For a DRAM cell to store two bits using a single cell capacitor, the cell capacitor should store one of four voltage values  $V_{cell0}$ ,  $V_{cell1}$ ,  $V_{cell2}$  or  $V_{cell3}$ , wherein  $V_{cell0}$  represents the lowest and  $V_{cell3}$  represents the highest cell voltage. To differentiate between the voltages, mid-point voltages  $V_{ref1}$ ,  $V_{ref2}$  and  $V_{ref3}$  are defined, as shown in FIG. 1. It may be seen that if the lowest actual cell voltage  $V_{cell0}$  is  $V_{SS}$  or zero,  $V_{ref1}$  is one-sixth the highest voltage  $V_{DD}$ ,  $V_{cell1}$  is one-third  $V_{DD}$ ,  $V_{ref2}$  is one-half  $V_{DD}$ ,  $V_{cell2}$  is two-thirds  $V_{DD}$ ,  $V_{ref3}$  is five-sixths  $V_{DD}$  and  $V_{cell3}$  equals  $V_{DD}$ . Thus it





In step 1, sub-bitlines  $BL_A$  and  $BL_B$  are disconnected from the  $V_{ref2}$  reference voltage, connected together and the sense amplifiers are not connected to the bitline. The cell capacitor 11 then dumps its charge onto the BL line formed of conductors  $BL_A$  and  $BL_B$ , resulting in a voltage which for example is

$$\left[ \frac{V_{DD}}{2} + \frac{C_s(V_{cell2} - V_{REF2})}{C_s + C_{BL}} \right] \text{ i.e. } \frac{V_{DD}}{2} + \frac{C_s}{C_s + C_{BL}} + \frac{2V_{DD}}{3}$$

$$\frac{V_{DD}}{2} + \frac{C_s(V_{cell2} - V_{REF2})}{C_s + C_{BL}}$$

where  $C_s$  is the cell capacitance and  $C_{BL}$  is the capacitance of the entire bitline.

The voltage  $V_{ref2}$  which is  $\frac{1}{2} V_{DD}$  is applied to the  $BL^*$  conductors  $BL^*_A$  and  $BL^*_B$ .

In step 2, the two halves of the BL conductor are separated, and the bit 1 sense amplifier is connected to sense the voltage on conductor  $BL_B$  to determine whether it is above or below the voltage  $V_{ref2}$  which is on the  $BL^*_B$  conductor. Since the voltage is  $V_{cell2}$  which is above  $V_{ref2}$ , a logic level one signal is stored in dummy cell 17 which is connected to the  $BL_B$  lead.

In step 3 the sense amplifier 15 and dummy cell 17 are disconnected from the bitline, and charge storage Ccell capacitor 18 is connected to lead  $BL_B$ . Conductors  $BL_B$ ,  $BL^*_B$ , and  $BL^*_A$  are all connected together, and the midpoint voltage  $V_{ref2}$  is applied thereto.

In step 4 the logic level signal stored in dummy cell 17 is dumped to the sub-bitlines  $BL_B$ ,  $BL^*_B$  and  $BL^*_A$ . The charge is also shared with Ccell 18, which has one half the capacitance of a normal cell. This charge sharing on the three half bitlines plus Ccell creates the exact reference level needed for the 2nd phase of sensing.

The total capacity of the Ccell 18 should be established so that the resulting voltage on the sub-bitlines is, in this example,  $V_{ref3}$ . Thus for example if the voltage on the Ccell and sub-bitlines was established at  $V_{ref2}$ , one-half  $V_{DD}$  in step 3, with the charge on dummy cell 17 having been established with full logic level  $V_{DD}$  in step 2, when it is connected to the combined sub-bitlines in step 4, its charge, being shared with the Ccell, should result in a voltage

$$\left( \frac{V_{DD}}{3} \right) \frac{C_s}{C_s + C_{BL}} + \frac{V_{DD}}{2}$$

i.e.  $V_{ref3}$ , which is midway between  $V_{cell2}$  and  $V_{cell3}$ .

On the other hand, if in step 2 the sensed bit was a zero, charge on dummy cell 17 would have been zero or  $V_{ss}$ . When connected to the combined bitlines in step 4 it would receive charge from the Ccell 18, causing a reduction in voltage to  $V_{ref1}$ , which is midway between  $V_{cell1}$  and  $V_{cell3}$ . Thus it may be seen that the combined sub-bitlines form a reference line, the voltage of which can be compared with that on cell 11, and corresponds to reference line 3A, 7B described with reference to FIG. 2.

In step 5 the Ccells 18 and dummy cell 17 are disconnected and each of the sub-bitlines are isolated. The voltage  $V_{ref2}$  of one-half  $V_{DD}$  is applied to the sub-bitline  $BL^*_B$ . It may be seen that the sub-bitline  $BL^*_B$  is now at the midpoint  $V_{ref2}$ , both sub-bitlines  $BL^*_A$  and  $BL_B$  are at the reference line voltage  $V_{ref3}$  (or  $V_{ref1}$  if the original cell voltage had been below  $V_{ref2}$ ), and the sub-bitline  $[BL_A] BL_A$  is at the cell capacitor 11 voltage.

FIG. 4 illustrates in steps 7 and 8 a write or restore operation.

It should be noted that the concept described above has certain very significant advantages. For example no changes are required to either the currently used DRAM basic memory cell or to the DRAM manufacturing process.

Reference is now made to FIGS. 5 and 6. In FIG. 5, a schematic diagram of an embodiment of the present invention is shown. The convention is used of the bitline conductors referenced in FIG. 4, that is  $BL_A$ ,  $BL^*_A$ ,  $BL_B$  and  $BL^*_B$ . All of the transistors used in this embodiment are N channel field effect transistors (FETs). While steps 1-6 are described in detail, a person understanding the description below will be able to understand how the restore and write operations proceed without further explanation.

Conductors  $BL_A$  and  $BL_B$  and  $BL^*_A$  and  $BL^*_B$  are connected to respective source and drains of FET transistors 20 and 21 respectively, whose gates are driven by timing signals  $CB_L$  and  $CB_L^*$  respectively. Bitline conductor  $BL_B$  is connected to a terminal of sense amplifier 22 via the source-drain circuit of FET transistor 23, while bitline conductor  $BL_A$  is connected to sense amplifier 24 via FET 25. Similarly bitline conductor  $BL^*_B$  is connected to the other terminal of sense amplifier 22 via FET 26 and bitline conductor  $BL^*_A$  is connected to the other terminal of sense amplifier 24 via FET 27. FETs 23 and 26 are operated via a timing signal ISO2 which is applied to their gates, and FETs 25

The timing voltage ISO2 then drops, causing transistors 23 and 26 to isolate the bitline conductors  $BL_B$  and  $BL_{\cdot B}$  from sense amplifier 22. The timing voltages EQ2,  $M_{A2}$  and  $M_{A2\cdot}$  then go high, causing transistor 34 to conduct and short-circuiting bitline conductors  $BL_B$  and  $BL_{\cdot B}$ , and causing FETs 31 and 30 to conduct, allowing reference voltage  $V_{BLP}(V_{ref})$  to be reapplied to the bitline conductors  $BL_B$  and  $BL_{\cdot B}$ . Then the timing voltage  $CBL_{\cdot}$  goes high, causing transistor 21 to conduct, joining bitline conductors  $BL_{\cdot A}$  with  $BL_{\cdot B}$  and  $BL_B$ . Accordingly the reference voltage  $V_{BLP}$  is applied to those three bitline conductors, which are equalized.

A person understanding this invention may now conceive of alternative structures and embodiments or variations of the above. All of those which fall within the scope of the claims appended hereto are considered to be part of the present invention.

(a) sensing whether or not the data voltage is above or below a voltage level midway between a highest and a lowest of said four levels,

(c) sensing whether the data voltage is higher or lower than the reference line, whereby which of the four levels the data occupies is read.

3. A method as defined in claim 1 in which said four levels are at 0,  $\frac{1}{3}$ ,  $\frac{2}{3}$  and 1 times a power supply voltage scaled by the cell to bitline capacitance ratio, and in which the voltage on the reference line in step (b) is set at either  $\frac{1}{6}$  or  $\frac{5}{6}$  the power supply voltage in step (b) scaled by the cell to bitline capacitance ratio.

**5.** A method of processing data having one of plural levels stored in a DRAM cell capacitor comprising:

(b) maintaining the other conductor of said pair of conductors split into other sub-bitline conductors and charging each of said other sub-bitline conductors to an intermediate voltage,

(d) sensing one of said sub-bitline conductors to determine whether the charge of said cell has a higher voltage than the intermediate voltage of one of said

(e) storing said logic level result signal in a dummy cell capacitor,

(g) dumping charge stored in the dummy cell capacitor on said sub-bitlines conductors other than the first sub-bitline conductor to which the charge of the cell capacitor was dumped, and on said charge storage capacitor together, thereby varying the predetermined voltage stored thereon to a degree related to the capacities of said dummy cell capacitor, said charge storage capacitor and said predetermined voltage, to a level above or below the intermediate level.

(i) applying said intermediate voltage to one of said other sub-bitline conductors.

whereby said first and second logic bits are indicative of one of four states corresponding to one of said plural levels stored in the DRAM cell.

7. A method as defined in claim 6 in which said intermediate and predetermined voltages are the same midpoint voltage between a highest and lowest voltage state representative of four logical states.

8. A method as defined in claim 7, including the further steps of short circuiting two or three of the sub-bit-lines to share charge thereon and establish a common voltage level, and storing said shared charge corresponding to the common voltage level on said cell, whereby a restore or write operation results.

9. A method as defined in claim 7, including the further steps of writing logic voltage levels to each of the sub-bitline conductors, short circuiting two or three of the sub-bitlines to share charge thereon and establish a common voltage level, and storing said shared charge corresponding to the common voltage level on said cell, whereby a write operation results.

✻ ✻ ✻ ✻ ✻

10. A method for storing a multi-bit value in a DRAM cell, the method comprising:
  - storing a charge in a cell capacitor, the stored charge producing one of a plurality of data voltage values;
  - precharging subbitlines of a pair of bitlines to one of a plurality of predetermined reference voltage levels;
  - dumping the stored charge onto a precharged subbitline of at least one pair of subbitlines to produce a sensing voltage;
  - determining a bit of the multi-bit value by comparing the sensing voltage to the reference voltage;
  - for each additional bit,
    - adjusting the reference voltage responsive to last determined bit; and
    - determining the additional bit by comparing the sensing voltage to the adjusted reference voltage.
11. The method of Claim 10, wherein adjusting the reference voltage comprises:
  - storing a charge in a dummy capacitor, said charge being indicative of previously determined bits;
  - charging at least one second cell capacitor to a reference voltage; and
  - dumping the charge stored in the dummy capacitor onto a plurality of subbitlines, and sharing said charge with the at least one second cell capacitor, the at least one second cell capacitor having a capacitance such that the adjusted reference voltage is established, said adjusted reference voltage being one of the plurality of predetermined reference voltage levels
12. The method of Claim 10, wherein the pair of bitlines is divided into a number of subbitlines, said number responsive to the number of data voltage values.
13. The method of Claim 10, wherein the DRAM cell is capable of operating in either of two modes, a first mode being as a one bit per cell DRAM, and a second mode being as a multibit per cell DRAM.
14. The method of Claim 10, wherein adjusting the reference voltage is in the direction of a last sensed bit.
15. A multi-bit DRAM cell, comprising:
  - a cell capacitor in which one of a plurality of voltage values is maintained;
  - means for precharging subbitlines of a pair of bitlines, the pair of bitlines being subdivided into a plurality of subbitlines
  - a plurality of switches for interconnecting the subbitlines;
  - a plurality of sensing amplifiers, each sensing amplifier associated with and switchably connected to a pair of subbitlines;
  - means for dumping the stored charge onto a precharged subbitline of at least one pair of subbitlines to produce a sensing voltage; and
  - means for adjusting the reference voltage responsive to a last determined bit.

16. The multi-bit DRAM cell of Claim 15, wherein switches are FET switches.
17. The multi-bit DRAM cell of Claim 16, wherein means for adjusting the reference voltage comprises:  
a dummy capacitor, in which a charge indicative of previously determined bits is stored; and  
at least one second cell capacitor having a capacitance such that upon dumping the charge stored in the dummy capacitor into said at least one second cell capacitor, the adjusted reference voltage is established, said adjusted reference voltage being one of the plurality of predetermined reference voltage levels.
18. The multi-bit DRAM cell of Claim 16, wherein the pair of bitlines is divided into a number of subbitlines, said number responsive to the number of data voltage values.
19. The multi-bit DRAM cell of Claim 16, wherein the DRAM cell is capable of operating in either of two modes, a first mode being as a one bit per cell DRAM, and a second mode being as a multibit per cell DRAM.

::ODMA\HODMA\IMANAGE\154908:1

005437-00400



**ABSTRACT**

A method of processing data having one of four voltage levels stored in a DRAM cell is comprised of sensing whether or not the data voltage is above or below a voltage level midway between a highest and a lowest of the four levels, setting the voltage on a reference line higher than the lowest and lower than the next highest of the four levels in the event the data voltage is below the midway voltage level, and setting the voltage on the reference line higher than the second highest and lower than the highest of the four levels in the event the data voltage is above the midway point, and sensing whether the data voltage is higher or lower than the reference line, whereby which of the four levels the data occupies is read.

000000-23275300




FIG. 1





FIG. 2








FIG. 5




FIG. 6

16135918148;#21/27

..ODMA\HODMA\UManager;139772;1

# PATENT APPLICATION

Docket No.: 2037.1005-002

JMS/GMB/dlc  
August 16, 2000

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

**Applicant:** Peter B. Gillingham

Reissue Application of U.S. Patent 5,283,761, Issued February 1, 1994

For: **METHOD OF MULTI-LEVEL STORAGE IN DRAM AND APPARATUS THEREOF (as amended)**

Date: 8-29-00

EXPRESS MAIL LABEL NO. EL531544795US

**DECLARATION AND POWER OF ATTORNEY**  
**FOR CONTINUATION OF REISSUE PATENT APPLICATION**

The Assistant Commissioner  
for Patents  
Washington, DC 20231

Sir:

As inventor of U.S. Patent No. 5,283,761, I hereby declare that:

1. My residence, post office address and citizenship are stated below next to my name.
2. I believe that I am the first and original inventor of the claimed subject matter described in United States Patent No. 5,283,761 granted on February 1, 1994 (hereinafter the '761 patent) entitled METHOD OF MULTI-LEVEL STORAGE IN DRAM for which a reissue patent is sought.

08/595,020

-2-

3. I have reviewed and I understand the contents of the specification of the subject reissue application, including the claims.
4. I hereby claim the benefit under 35 U.S.C. 120 of any United States application(s), or 365(c) of any PCT international application designating the United States of America, listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States or PCT International application in the manner provided by the first paragraph of 35 U.S.C. 112, I acknowledge the duty to disclose information known by me to be material to patentability as defined in 37 C.F.R. 1.56 which became available between the filing date of the prior application and the national or PCT international filing date of this application:

(Application Serial No.)	(Filing date)	(Status: patented, pending, abandoned)
<u>08/595,020</u>	<u>January 31, 1996</u>	<u>Pending (Allowed)</u>

5. I believe the original '761 patent is wholly or partly inoperative or invalid by reason of my claiming less than I had a right to claim in the patent.
6. One error being relied upon as a basis for reissue is that the original claims 1-9 failed to claim an embodiment in which a DRAM cell is capable of operating as either a one-bit-per-cell DRAM or as a multi-bit-per-cell DRAM, as disclosed in the original '761 patent at column 2, lines 54-56.
7. All errors being corrected in the reissue application, including all amendments up to the time of and with the filing of this Declaration, arose without any deceptive intention on the part of the applicant.



08/595,020

-3-

8. As a named inventor, I hereby appoint the attorneys and/or agents associated with

Hamilton, Brook, Smith & Reynolds, P.C., Two Militia Drive,  
Lexington, Massachusetts 02421-4799 - Customer No. 21005,

to prosecute this application and to transact all business in the Patent  
and Trademark Office connected therewith.

Please send correspondence to:

Customer No. 21005

HAMILTON, BROOK, SMITH & REYNOLDS, P.C.  
Two Militia Drive  
Lexington, MA 02421-4799

Direct telephone calls to: Mary Lou Wakimura, Telephone No.: 781-861-6240

Direct facsimiles to: Mary Lou Wakimura, Telephone No. 781-861-9540

08/595,020 23/27

08/595,020

-4-

9. I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

Name: Peter B. Gillingham

Signature: Peter B. Gillingham

Date: 21 August 2000

Residence: 43 Slade Crescent  
Kanata, Ontario, Canada K2K 2K9

Citizenship: Canadian

Post Office Address: 43 Slade Crescent  
Kanata, Ontario, Canada K2K 2K9

007000-2949900

CERTIFICATE UNDER 37 C.F.R. § 3.73(b)Applicant(s): Peter B. GillinghamApplication No.: 08/595,020Filed: January 31, 1996For: METHOD OF MULTI-LEVEL STORAGE IN DRAM AND APPARATUS THEREOF (as amended)MOSAID TECHNOLOGIES INCORPORATED

(Name of Assignee)

, a corporation

(Type of Assignee, e.g., corporation, partnership, university, government agency, etc.)

certifies that it is

- A. ☒ the assignee of the entire right, title and interest in the patent application identified above.
- B. ☐ an assignee together with [ ] of the entire right, title and interest in the patent application identified above. A separate Certificate under 37 CFR § 3.73(b) is attached.

The right, title and interest of the above-named assignee in the patent application identified above is established by virtue of:

- A. ☒ An assignment from the inventor(s) of the patent application identified above. The assignment was recorded in the Patent and Trademark Office at Reel 6207, Frame 647, or for which a copy thereof is attached.

OR

- B. ☐ A chain of title from the inventor(s) of the patent application identified above, to the current assignee as shown below:

1. From: \_\_\_\_\_ To: \_\_\_\_\_  
The document was recorded in the Patent and Trademark Office at  
Reel \_\_\_\_\_, Frame \_\_\_\_\_, or for which a copy thereof is attached.
2. From: \_\_\_\_\_ To: \_\_\_\_\_  
The document was recorded in the Patent and Trademark Office at  
Reel \_\_\_\_\_, Frame \_\_\_\_\_, or for which a copy thereof is attached.
3. From: \_\_\_\_\_ To: \_\_\_\_\_  
The document was recorded in the Patent and Trademark Office at  
Reel \_\_\_\_\_, Frame \_\_\_\_\_, or for which a copy thereof is attached.

[ ] Additional documents in the chain of title are attached.

[ ] Copies of assignments or other documents in the chain of title are attached.

The undersigned (whose title is supplied below) is empowered to act on behalf of the assignee.

I hereby declare that all statements made herein of my own knowledge are true, and that all statements made on information and belief are believed to be true; and further, that these statements are made with the knowledge that willful false statements and the like so made, are punishable by fine or imprisonment, or both, under Section 1001, Title 18 of the United States code, and that such willful false statements may jeopardize the validity of the application or any patent issuing thereon.

Date: 21 August 2000Name: ~~George Cwynar~~ Peter GillinghamTitle: President VP Business DevelopmentSignature: Peter Gillingham